



2-wire transmitter with HART protocol

5335A

- -RTD, TC, Ohm, or mV input
- Extremely high measurement accuracy
- HART 5 protocol
- Programmable sensor error value
- For DIN form B sensor head mounting























Application

- · Linearized temperature measurement with Pt100...Pt1000, Ni100...Ni1000, or TC sensor.
- Difference or average temperature measurement of 2 resistance or TC sensors.
- · Conversion of linear resistance variation to a standard analog current signal, for instance from valves or Ohmic level sensors.
- · Amplification of a bipolar mV signal to a standard 4...20 mA current signal.
- · Connection of up to 15 transmitters to a digital 2-wire signal with HART communication.

Technical characteristics

- Within a few seconds the user can program PR5335A to measure temperatures within all ranges defined by the norms.
- The RTD and resistance inputs have cable compensation for 2-, 3and 4-wire connection.
- The 5335A has been designed according to strict safety requirements and is therefore suitable for application in SIL
- · Continuous check of vital stored data for safety reasons.
- · Sensor error detection according to the guidelines in NAMUR NE89.

Mounting / installation

• For DIN form B sensor head or DIN rail mounting with the PR fitting type 8421.

Applications 2-wire installation in control room RTD to 4...20 mA (mA) 2-wire installation TC to 4...20 mA in control room -V+ (mA) 2-wire installation Resistance to 4...20 mA in control room mA 2-wire installation in control room mV to 4...20 mA v+ (mA) 2-wire installation Difference or average in control room RTD, TC or mV

Order

Туре	Version	
5335	Zone 2 / Div. 2	; A

-40°C to +85°C 2028°C < 95% RH (non-cond.) IP68 / IP00
Ø 44 x 20.2 mm 50 g 1 x 1.5 mm ² stranded wire 0.4 Nm IEC 60068-2-6 ±1.6 mm ±4 g
8.035 VDC
1.5 kVAC / 50 VAC
160 s 30 s Loop Link & HART > 60 dB Better than 0.05% of selected range 22 bit 16 bit < 0.005% of span / VDC < ±0.1% of span < ±1% of span

Input specifications Common input specifications			
Max. offset	50% of selected max. value		
RTD type	Pt100 Ni100 lin R		
Cable resistance per wire	$5~\Omega$ (up to $50~\Omega$ per wire is possible with reduced measurement accuracy)		
Sensor current	Nom. 0.2 mA		
Effect of sensor cable resistance (3-/4-wire)	< 0.002.0 / 0		
Sensor error detection			
TC input			
Thermocouple type	B, E, J, K, L, N, R, S, T, U, W3, W5		
Cold junction compensation (CJC)	< ±1.0°C		
Sensor error detection			
Sensor error current: When	100		
detecting / else	Nom. 33 μA / 0 μA		
Voltage input			
Measurement range			
Min. measurement range (span)			
Input resistance	10 ΜΩ		
Output specifications			
Current output Signal range	4 20 m∆		
Min. signal range			
Load (@ current output)			
Load stability	≤ 0.01% of span / 100 Ω		
Sensor error indication	•		
NAMUR NE43 Upscale/Downscale			
of span	= of the presently selected range		
I.S. / Ex marking			
ATEX	II 3 G Ex nA [ic] IIC T6T4 Gc, II 3 G Ex ec [ic] IIC T6T4 Gc, II 3 G Ex ic IIC T6T4 Gc, II 3 D Ex ic IIIC Dc		
IECEx	Ex nA [ic] IIC T6T4 Gc, Ex ec [ic] IIC T6T4 Gc, Ex ic IIC T6T4 Gc, Ex ic IIIC Dc		
CSA			
INMETRO	Ex ec [ic] IIC T6T4 Gc, Ex ic		
	IIC T6T4 Gc, Ex ic IIIC Dc		
Observed authority requirements			
EMC	2014/30/EU & UK SI 2016/1091		
ATEX			
RoHS			

EAC Ex..... TR-CU 012/2011

Approvals

ATEX..... DEKRA 20ATEX0109X SIL Hardware assessed for use in SIL applications